



CPA900

WIRELESS MICROPHONE SERIES



TRANSMITTER

(Handheld / Bodypack)

- Channels: 200 channels
- Bandwidth: 50MHz
- Channel Space: 250KHz
- Frequency stability: 0.005%
- FM Max frequency adjustment: 45KHz
- RF output: HIGH 10mW / LOW 5mW
- Power Supply: 2*AA batteries

RECEIVER

- Operating Frequency: 470-786MHz
- Channels: 2*100 channels
- Bandwidth: 50MHz
- Channel Space: 250KHz
- ACR/IR SYNC & scan technology
- Battery display on LCD
- S/N Ratio: >105dB
- T.H.D Distortion: <0.5%
- Frequency response: 20Hz – 18KHz
- True diversity, distance: 80-100meters approx.

